



Touchstone® WBM760B EuroDOCSIS™ 3.0 Cable Modem Technical Specification

Specifications

Physical

Operating Temperature °C (°F)	+5 to +40 (+41 to +104)
Operating Relative Humidity (Min-Max)	5-95%(Non condensing)
Storage Temperature °C (°F)	-40 to +70 (-40 to +158)
Dimensions (HxWxD) in. (cm)	7.1 x 1.7 x 5.9 (18.0 x 4.3 x 15.0) - excluding F-connector
Weight lbs (kg)	1.0 (0.46)
Diagnostic LEDs	Power, DS, US, Online, Link
Operating Temperature °C (°F)	+5 to +40 (+41 to +104)

Interfaces

RF Interface	External 'F' type connector
Ethernet Interfaces (bridged)	10/100/1000 Base-T Ethernet RJ-45
USB Interface (bridged)	High Speed (480Mbps) USB 2.0
Input Voltage (nominal)	115-240 VAC 50/60 Hz
Power Consumption (W)	7 (idle), 9 (max.)

RF Downstream

Frequency Range (MHz)	108 to 1002
Bonded Channels	up to 4
Capture Bandwidth (MHz)	96 (typical)
Carrier Bandwidth (MHz)	8
Modulation (QAM)	64 or 256
Data Rate (Mbps)	up to 220
RF Input Sensitivity Level (dBmV)	-17 to +17
Total Input Power (80 to 1002 MHz, dBmV Max.)	33

Specifications Continued

RF Upstream

Frequency Range (MHz)	5-65
Bonded Channels	Up to 4
Modulation	QPSK, 8 QAM, 16 QAM, 32 QAM, 64 QAM & 128 QAM (S-CDMA only)
Data Rate (Mbps) (Max.)	up to 122
RF Output Level (dBmV – one channel)	
A-TDMA	+17 to 57 dBmV (32 QAM, 64 QAM); +17 to 58 dBmV (8 QAM, 16 QAM); +17 to 61 dBmV (QPSK) <i>Note: A-TDMA max output power reduced 3dB when transmitting two channels and 6dB when transmitting 3 or 4 channels.</i>
S-CDMA	+17 to +56 dBmV (all modulations) <i>Note: S-CDMA max output reduced 3dB when transmitting 2 or more channels.</i>
Automatic Level Adjust	Yes
Frequency Stability (kHz)	±5
Output Impedance (Ohms)	75

Standards

EuroDOCSIS 3.0 / DOCSIS 3.0
CE, CB
RoHS, WEEE
IEEE 802.3, IEEE 802.3ab
WHQL, USB-IF

Ordering Information

Part Number	Description
780133	Touchstone WBM760B/CE EuroDOCSIS 3.0 complaint data-only cable modem with integrated 115-240 VAC, 50/60 HZ power supply 6 foot CEE 7/16 European power cord. Includes Quick Install Guide, Ethernet Cable, USB Cable, and CD-ROM with user's guide and USB drivers

Specifications are subject to change without notice.

The capabilities, system requirements and/or compatibility with third-party products described herein are subject to change without notice. ARRIS, the ARRIS logo, Auspice®, C3™, C4®, C4c™, Cadant®, C-COR®, CHP Max®, ConvergeMedia™, Cornerstone®, CXM™, D5™, Digicon®, Flex Max®, Keystone™, MONARCH®, n5™, nABLE™, NSM™, nVision®, OpsLogic®, OpsLogic Service Visibility Portal™, PLEXIS®, PowerSense™, Regal®, ServAssure™, Service Visibility Portal™, TeleWire Supply®, TLX®, Touchstone®, VoiceAssure™, VSM™, and WorkAssure™ are all trademarks of ARRIS Group, Inc. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and the names of their products. ARRIS disclaims proprietary interest in the marks and names of others. © Copyright 2009 ARRIS Group, Inc. All rights reserved. Reproduction in any manner whatsoever without the express written permission of ARRIS Group, Inc. is strictly forbidden. For more information, contact ARRIS.



www.arrisi.com